

Watch Movement Specification and Drawing

CHRONOGRAPH

Cal. VR34B

Movement Size

13 1/2""

Casing Diameter


Ø 30.6mm

Height

3.97mm

Battery Life

3 years



Date: 7/Aug./'20

Cal. VR34B

Items	Rev.	Page
Specifications	01	1
Appearance	00	2
Casing	00	3
Hand fitting	01	4
Hand setting stem	00	5
Dial	00	6
Casing ring	00	7
Operation	00	8
Attention	00	9

Cal.

VR34B

Specifications

Date: 7/Aug./'20

Rev.: 01

Analog Quartz 13 1/2" Chronograph Movement

1. MOVEMENT DIMENSIONS

Outside diameter ϕ 31.2mm \times 28.0mm(3-9H)

Casing diameter ϕ 30.6mm

Total height 3.97mm (including battery)

2. TIME STANDARD

Type of quartz oscillator Tuning fork Frequency of quartz oscillator 32,768 Hz

Accuracy ± 20 seconds per month (on wrist)

Operating temperature range -5° C to $+50^{\circ}$ C Regulation device Nil (Pre-adjusted)

3. INDICATOR / FUNCTIONS

3 Hands Hour / Minute / Second

Small hands 24 hour(2H) / Second chronograph(6H) / Minute chronograph(10H)

Calendar Instant setting device for date calendar

Reset switch

Power depletion warning function (BLD) (Second hand moves at 2-second intervals)

Setting mechanism Crown at normal position : Free

Crown pulled out 1st click : Instant date change
Crown pulled out 2nd click : time setting / reset
1/1 second up to 30 minutes with split time measurement

4. FEATURES

Chronograph

Jewels 0 Jewels

Anti-magnetism Over 1600A/m (Direct current magnetic field) Maximum unbalance of hands Hour hand : $0.6 \,\mu\,\text{N} \cdot \text{m}$

Minute hand $0.9 \mu \text{ N} \cdot \text{m}$ Second hand $0.09 \mu \text{ N} \cdot \text{m}$ 24 hour hand $0.05 \mu \text{ N} \cdot \text{m}$ Second chronograph hand $0.05 \mu \text{ N} \cdot \text{m}$ Minute chronograph hand $0.05 \mu \text{ N} \cdot \text{m}$

Moment of Inertia Second hand : less than $0.35 \,\mu\,\mathrm{g}\cdot\mathrm{m}^2$

Second chronograph hand : less than $0.05 \mu \,\mathrm{g} \cdot \mathrm{m}^2$

5. BATTERY

Type / Size Silver oxide battery / ϕ 9.5mm × t 2.0mm Recommended battery SR920SW (Maxell, Murata, Seizaiken)

Nominal voltage 1.55 V

Battery life Approx. 3 years Driving current consumption Approx. $1.2 \mu A$

Operation stopping voltage 1.4V (Chronograph function)

6. SEPARATED PARTS (Parts code)

Hand setting stem 0351578 or 0351177

Battery SR920SW

7. TEST OF ACCURACY

Equipment to be used SEIKO quartz tester QT-99,

Greiner quartz timer-C, Witschi Q-tester 4000

Duration of measurement 10 seconds


All specifications are subject to change without notice.

cal. VR34B

Appearance

Date:19/Oct./'18

Rev.:00




Cal. VR34B

Casing

Date:19/Oct./'18


Rev.:00



Center post	Type M (2) VR34B**	
Maximum height from dial support	H1	225
Total height including movement	Н2	622
Maximum height from dial support	Н3	70

- <u>*1:First pullout stroke</u>
- ★2:Second pullout stroke
- <u>* 3:Button stroke</u>
- <u>★4:Switching stroke</u>
- ★5:The earth spring is absolutely placed in contact with the case back.

1515(From Mov't center) *3 83.9



Cal. VR34B

Hand fitting

Date: 1/Feb./'19


Rev.:01




- $\leq 0.6\mu \text{ N} \cdot \text{m} \quad \begin{pmatrix} 60\mu \text{ g} \cdot \text{m} \\ 90\mu \text{ g} \cdot \text{m} \end{pmatrix}$ $\leq 0.9\mu \text{ N} \cdot \text{m} \quad \begin{pmatrix} 90\mu \text{ g} \cdot \text{m} \\ 90\mu \text{ g} \cdot \text{m} \end{pmatrix}$ $\leq 0.05\mu \text{ N} \cdot \text{m} \quad \begin{pmatrix} 5\mu \text{ g} \cdot \text{m} \\ 5\mu \text{ g} \cdot \text{m} \end{pmatrix}$ $\leq 0.05\mu \text{ N} \cdot \text{m} \quad \begin{pmatrix} 5\mu \text{ g} \cdot \text{m} \\ 5\mu \text{ g} \cdot \text{m} \end{pmatrix}$ · Hour hand · Minute hand
- · Second hand · Second chronograph hand $\leq 0.05\mu$ N·m (· Minute chronograph hand $\leq 0.05\mu$ N·m (
- · 24 hour hand

Moment of inertia

· Second hand \leq 0.35 μ g·m² · Second chronograph hand $\leq 0.05\mu \text{ g} \cdot \text{m}^2$



	Parts No.					
					Minute counting wheel	
Type M (2) VR34B**	0271661	0221662	0241604	0888510	0888520	1002561



■1:It is the size taken into consideration for hands attachment.

Please observe some standard value specified in unbalance and moment of inertia when using long hands.


Unit : 1=1/100mm

Ρ. 4 cal. VR34B

Hand setting stem

Date:19/Oct./'18

Rev.:00




≫ Not threaded

	Part No.	S1	S2	* S3
Type-1	0351177	1366	1964	60
Type-2 (Standard)	0351578	2507	3105	650

Material : Steel

Hardness: Vickers 600±50

Unit: 1=1/100mm P. 5



Unit: 1=1/100mm P. 6

Cal. VR34B Date:19/Oct./′18 Casing ring Rev.:00 12H Ø3120±3 R100 R100 1550 450 450 3H 450 2800 ±3 _R100 R100 1403 1403 1374 A-Asection _(ø3359) 20 ø3068 ø3228 <u>C view</u> <u>D view</u> <u>B view</u> 450 ±5 _1,30 ±3_ 200 ±3 152

Unit : 1=1/100mm

P. 7


Cal.

VR34B

Operation

Date: 19/Oct./'18

Rev.: 00




	Crown position		
	0 click	1st click	2nd click
Crown	Free	Turn counterclockwise for date change	Time setting
2H button	Chronograph Start/Stop Restart	Chronograph Start/Stop Restart	Chronograph hands 0-setting (clockwise)
4H button	Chronograph Reset Split Split release	Chronograph Reset Split Split release	Chronograph hands 0-setting (counterclockwise)


Chronograph function

Second chronograph hand is capable of timing 30 minutes. (60 seconds x 30 times) Minute chronograph hand is capable of timing 30 minutes.


■ Standard measurement




■ Accumulated elapsed time measurement



■ Split time measurement



■ Measurement of two competitors



Cal.

VR34B

Attention

Date: 19/Oct./'18

Rev.: 00

1. Case

Please use the metal case back to prevent from the movement mal-function by static electricity.


2.Hour Wheel

When set and remove the hour hand repeatedly, it may reduce the hand fixing torque because the hour wheel is made by plastic.

To ensure the enough fixing torque, it isn't recommended to re-assemble the hour hand more than five times.

3. Button position

Please keep the clearance between the movement and the tip of button to prevent the interference in assembling and enable to be cased smoothly.



To keep the clearance, it is recommended to use button spring.